

NON-VOLATILE SEMICONDUCTOR MEMORY DEVICE ADAPTED  
TO STORE A MULTI-VALUED DATA IN A SINGLE MEMORY CELL  
CROSS-REFERENCE TO RELATED APPLICATIONS

10 BACKGROUND OF THE INVENTION

This invention relates to an electrically data rewritable non-volatile semiconductor memory device. More particularly, it relates to a multi-value flash memory adapted to store a multi-valued data in a memory cell.

In a flash memory, the accumulated electric charge of the floating gate of a memory cell transistor is changed as the stored data is erased and a new data is written there. Then, as a result, the threshold value is changed to store the data. For instance, the negative threshold value may be made to corresponds to a "1" data, whereas the positive threshold value may be made to corresponds to a "0" data.

In recent years, multi-value flash memories adapted to store a plurality of bits in a single memory

cell have been developed to reduce the cost per bit and/or increase the storage capacity. In a memory device adapted to store two bits in a single memory cell, the memory cell has four threshold values  
5 depending on the data to be stored there.

A highly reliable memory device can be obtained by accurately controlling the threshold values of each memory cell. "Fast and Accurate Programming Method for Multi-level NAND EEPROMs, pp. 129-130, Digest of 1995  
10 Symposium on VLSI Technology" proposes a method of writing data, raising the write voltage  $V_{pgm}$  at a rate, in order to precisely control the threshold values of each memory cell.

With the method proposed in the above cited  
15 document, the width of distribution of each threshold value can be controlled theoretically to as small as 0.2V by raising the write voltage  $V_{pgm}$  at a rate of 0.2V/10  $\mu$ sec. Normally, the write voltage  $V_{pgm}$  is divided into a plurality of write pulses and the  
20 voltage  $V_{pgm}$  of the pulses is raised stepwise at a predetermined rate. This technique provides an effect similar to that of continuously raising the write voltage  $V_{pgm}$ . The threshold value is checked after applying each pulse to the memory cell and the write  
25 operation is terminated when the threshold value has got to a predetermined verification level.

Meanwhile, micronization of processing dimensions

is in progress. This means that the gaps separating memory cells are made smaller and smaller to consequently give rise to various problems from the viewpoint of multi-valued flash memories.

5 For instance, the distance separating floating gates is reduced to produce problems as pointed out below as a result of micronization.

Imagine two memory cells A and B arranged side by side. Assume that the data of the two memory cells  
10 are erased simultaneously and they are made to have a threshold value of -3V. Then, firstly a data is written into the memory cell A. As a result, its threshold value may be raised to 0.5V to 1V. Subsequently, another data that is different from the  
15 data written into the memory cell A is written into the memory cell B. As the threshold value of the memory cell B is raised to 1.5V to 2V, the electric potential of the floating gate of the memory cell A falls and its threshold value is raised, say, to 1V to 1.5V as  
20 a result of the capacitive coupling of the floating gates of the two memory cells.

In the above described instance, the difference of the threshold values of the memory cells A and B (read out margin) should be at least 0.5V. However, it is  
25 reduced to 0V as a result of the capacitive coupling of the floating gates of the two memory cells. Thus, the difference of the threshold values necessary for

discriminating two different data is reduced and the read out margin disappears.

How the threshold value of a memory cell storing a data written in advance in a manner described above changes under the influence of a write operation of another memory cell will be described below by referring to FIGS. 1A through 1C of the accompanying drawing.

FIG. 1A shows the electric charge of the floating gate FG1 of a memory cell where the data stored there is erased and subsequently a new data is written. Electrons are accumulated in the floating gate FG1 of the memory cell where a data is written. In FIG. 1A, "- -" indicates electrons. Subsequently, data are written in the memory cells located respectively at the two sides of the first memory cell and having respective floating gates FG2, FG3. Then, a change occurs at the floating gate FG1 of the first memory cell as shown in FIG. 1B. The electric potential of the memory cell where a data is written first falls and its threshold value rises as shown in FIG. 1C because of the electrostatic capacitive coupling of the neighboring floating gates FG2, FG3. Then, as a result, the threshold value of the memory cell having the floating gate FG1 shows a wide distribution. In FIGS. 1A and 1B, reference symbol WL denotes the word line (control gate) arranged commonly for the

memory cells having the floating gates FG1, FG2, FG3.

Thus, the technological development for reducing the distribution width of the threshold value of a memory will become increasingly important in the future in order to cope with this problem.

It may be conceivable to reduce the stepwise increment  $Dv_{pgm}$  of the write voltage  $V_{pgm}$  in order to avoid this problem. For example, the distribution width of the threshold value is reduced from 0.5V to 0.1V to increase the write out margin by 0.4V by reducing the stepwise increment  $Dv_{pgm}$  from 0.5V to 0.1V.

However, as the stepwise increment is reduced to 1/5 of the original value, the number of pulses becomes five times as many as the original number. Then, the write time will become five times as long as the original value to give rise to a new problem.

Therefore, so far, any attempt at securing a write out margin and raising the reliability of a memory device is accompanied by the problem of an increased write time.

#### BRIEF SUMMARY OF THE INVENTION

In an aspect of the present invention, there is provided a non-volatile semiconductor memory device comprises: an electrically data rewritable non-volatile semiconductor memory cell; and a write circuit for writing data in the memory cell, the write circuit

writes a data in the memory cells by supplying a write voltage and a write control voltage to the memory cell, continues the writing of the data in the memory cell by changing the supply of the write control voltage to the memory cell in response to an advent of a first write state of the memory cell and inhibits any operation of writing a data to the memory cell by further changing the supply of the write control voltage to the memory cell in response to an advent of a second write state of the memory cell.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

FIGS. 1A through 1C are schematic illustrations of the sectional view and distribution of a threshold value referred to for pointing out the problem of the prior art;

FIG. 2 is a schematic block diagram of the first embodiment of flash memory according to the invention, illustrating its overall configuration;

FIG. 3A is a schematic block diagram illustrating the internal configuration of the memory cell array in FIG. 2;

FIG. 3B is a circuit diagram of a NAND-type memory unit arranged in each of the blocks of FIG. 3A;

FIG. 4 is a schematic cross sectional view of the memory cell array of FIG. 2 taken along the column direction to show the structure of the device;

FIGS. 5A and 5B are schematic cross sectional

views of the memory cell array of FIG. 2 taken along the row direction to show the structure of the device;

FIG. 6 is a schematic block diagram of a principal part of the column control circuit of FIG. 2,

5 illustrating its configuration;

FIG. 7 is a graph illustrating the relationship between a multi-valued data and the threshold value of a memory cell of the first embodiment of multi-value flash memory according to the invention;

10 FIG. 8 is a graph illustrating the changing threshold value of memory cells of a known flash memory and a data writing method adapted to use such a changing threshold value;

15 FIG. 9 is a graph illustrating the changing threshold value of a memory cell of the first embodiment of multi-value flash memory according to the invention and a data writing method adapted to use such a changing threshold value;

20 FIG. 10 is a graph illustrating the method for writing a higher order page data into a same memory cell and the change with time of the threshold value of the memory of the first embodiment;

25 FIG. 11 is a graph illustrating the signal waveforms of different parts of the first embodiment of flash memory according to the invention when writing a lower order page data into a single memory cell;

FIG. 12 is a flow chart schematically illustrating

the control algorithm of the first embodiment of flash memory according to the invention when writing a lower order page data into a single memory cell;

FIG. 13 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention when writing a higher order page data into a memory cell;

FIG. 14 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention for controlling the order of writing data into the blocks;

FIG. 15 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention when reading the lower order page data stored in a memory cell;

FIG. 16 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention when reading the higher order page data stored in a memory cell;

FIG. 17A is a graph illustrating the signal waveforms in a write step of the first embodiment of flash memory according to the invention;

FIG. 17B is a graph illustrating the signal waveforms in a write step of the second embodiment of flash memory according to the invention; and

FIG. 18 is a graph illustrating the signal waveforms of different parts of the third embodiment of



flash memory according to the invention when writing a data into a single memory cell.

#### DETAILED DESCRIPTION OF THE INVENTION

Now, the present invention will be described in greater detail by referring to the accompanying drawing that illustrates preferred embodiment of the invention.

FIG. 2 is a schematic block diagram of the first embodiment of multi-value flash memory according to the invention, illustrating its overall configuration;

Referring to FIG. 2, a plurality of flash memory cells, a plurality of bit lines and a plurality of word lines are arranged in the memory cell array 1. The flash memory cells are arranged in the form of a matrix.

A column control circuit 2 and a row control circuit 3 are arranged adjacently relative to the memory cell array 1. The column control circuit 2 controls the bit lines in the memory cell array 1 for erasing data from, writing data into and reading data from memory cells.

The row control circuit 3 is used for selecting a word line in the memory cell array 1 and supplying a voltage necessary for erasing, writing and reading data.

Additionally, a source line control circuit 4 for controlling source lines of the memory cell array 1 and a P-well control circuit 5 for controlling the p-type

wells for forming the memory cell array 1 are also arranged near the memory cell array 1.

Data input/output buffer 6 is connected to a host by way of an external I/O line. The data input/output  
5 buffer 6 is adapted to receive data to be written, outputs read out data and receive address data and command data. The data to be written received by the data input/output buffer 6 are forwarded to the column control circuit 2. The data input/output buffer 6  
10 receives the read out data from the column control circuit 2.

An external address data is sent to the column control circuit 2 and the row control circuit 3 by way of state machine 8 in order to select memory cells in  
15 the memory cell array 1.

A command data from the host is sent to command interface 7. The command interface 7 receives a control signal from the host and determines if the data input to the data input/output buffer 6 is a data to be  
20 written, a command data or an address data. If it is a command data, the command interface 7 forwards the command to the state machine 8 as received command signal.

The state machine 8 controls the overall operation  
25 of the flash memory. It receives a command from the host for controlling the operation of reading data, writing data and erasing data and also controls the

data input/output operation. The state machine 8 arranged a write counter PC for counting the number of data writing operations to each of the memory cells.

FIG. 3A is a schematic block diagram illustrating the internal configuration of the memory cell array 1 in FIG. 2. The memory cells of the memory cell array 1 are divided into a number of blocks BLOCK0 through BLOCK1023. A block is the smallest unit for an erasing operation. Each of the blocks BLOCK<sub>i</sub> (*i* = 0 through 1023) includes a total of 8,512 NAND type memory units as shown in FIG. 3B.

In this embodiment, each of the NAND type memory units contains four memory cells M that are connected in series and further to a bit line BLe or BLo at an end thereof by way of a selection gate S1 commonly connected to selection gate lines SGD *i* and to a common source line C-source at the opposite end thereof by way of a selection gate S2 commonly connected to selection gate lines SGS *i*.

Each memory cell M has a control gate, a floating gate, a source and a drain. The control gates of the four memory cell M of each NAND type memory unit are commonly connected to the corresponding one of the word lines WL0 *i* through WL3 *i*.

Data are independently written into and read out from the even-numbered bit lines BLe and the odd-numbered bit lines BLo as counted from 0. Data are

simultaneously written into or read out from 4,256 memory cells connected to the even-numbered bit lines BLe out of the 8,512 memory cells whose control gates are connected to a single word line WL.

5           When each memory cell stores a 1-bit data, the 4,256 bits data stored in 4,256 memory cells constitute a unit of page. Thus, when a single memory cell stores a 2-bit data, the 4,256 memory cells store data of two pages. Data of other two pages are stored in the 4,256  
10 memory cells connected to the odd-numbered bit lines BLo. Data are written into or read out from the memory cells of a same page simultaneously.

FIG. 4 is a schematic cross sectional view of the memory cell array 1 of FIG. 2 taken along the  
15 column direction to show the structure of the device. Referring to FIG. 4, an n-type well 11 is formed on a p-type substrate 10 and a p-type well 12 is formed in the n-type well 11. Each memory cell M comprises a source and a drain formed in an n-type diffusion  
20 layer 13, a floating gate FG arranged in a channel region between the source and the drain by way of a tunnel oxide film and a control gate CG arranged on the floating gate FG by way of an insulating film and operating as word line WL.

25           Each of the selection gates S1, S2 includes a source and a drain formed in the n-type diffusion layer 13 and a selection gate line SG having a two-layer

structure. Both the word line WL and the selection gate line SG are connected to the row control circuit 3 in FIG. 2 and controlled by the output signal from the row control circuit 3.

5           Each NAND type memory unit including four memory cells M and selection gates S1, S2 is connected at an end thereof to the metal wiring layer M0 of the first layer by way of a contact hole CB1. The metal wiring layer M0 is connected to the metal wiring layer M1 of  
10           the second layer operating as bit line BL by way of a via hole V1. The bit line BL is connected to the column control circuit 2 in FIG. 2.

          The NAND type memory unit is connected at the other end thereof to the metal wiring layer M2 of the  
15           first layer operating as common source line C-source by way of still another contact hole CB2. The common source line C-source is connected to the source line control circuit 4 in FIG. 2.

          An n-type diffusion layer 14 is formed on the  
20           surface of the n-type well 11, while a p-type diffusion layer 15 is formed on the surface of the p-type well 12. Both of the n-type diffusion layer 14 and the p-type diffusion layer 15 are connected to the metal wiring layer M3 of the first layer operating as well  
25           line C-p-well by way of respective contact holes CB3, CB4. The well line C-p-well is connected to the P well control circuit 5 in FIG. 2.

FIGS. 5A and 5B are schematic cross sectional views of the memory cell array 1 taken along the row direction to show the structure of the device. As shown in FIGS. 5A and 5B, each memory cell is isolated from the remaining memory cells by element isolations STI.

As shown in FIG. 5A, in each memory cell, a floating gate FG is laid on a channel region by way of a tunnel oxide film 16. A word line WL is laid on the floating gate FG by way of an insulating film 17 that is an ONO film.

As shown in FIG. 5B, the selection gate line SG has a two-layer structure. The upper layer selection gate line SG and the lower layer selection gate line SG are connected to an end of the memory cell array 1 or a predetermined number of bit lines.

FIG. 6 is a schematic block diagram of a principal part of the column control circuit 2 of FIG. 2, illustrating its configuration.

In the column control circuit 2, a data storage circuit 20 is arranged for every two bit lines including an even-numbered bit line BLe and an odd-numbered bit line BLo having a same column number. In the column control circuit 2, a sense amplifier is also arranged for the data storage circuit 20 in order to write data into and read data from memory cells.

Referring to FIG. 6, an n-channel MOS transistor

Qn1 is connected for column selection between the data storage circuit 20 and the even-numbered bit line BLe, whereas another n-channel MOS transistor Qn2 is connected for column selection between the data storage circuit 20 and the odd-numbered bit line BLo.

Either of the even-numbered bit line BLe or the odd-numbered bit line BLo connected to each data storage circuit 20 is selected and connected to the data storage circuit 20 to control the operation of writing a data or that of reading a data. More specifically, when signal EVENBL is at level H and signal ODDBL is at level L, the MOS transistor Qn1 is made electrically conductive to select the even-numbered bit line BLe, which bit line BLe is then connected to the data storage circuit 20. When, on the other hand, when signal EVENBL is at level L and signal ODDBL is at level H, the MOS transistor Qn2 is made electrically conductive to select the odd-numbered bit line BLo, which bit line BLo is then connected to the data storage circuit 20. Note that the signal EVENBL is supplied to all the n-channel MOS transistors for column selection connected to the even-numbered bit lines BLe, whereas the signal ODDBL is supplied to all the n-channel MOS transistors for column selection connected to the odd-numbered bit lines BLo. The unselected bit lines BL are controlled by some other circuit (not shown).

Each data storage circuit 20 includes three binary data storage sections DS1, DS2, DS3, of which the data storage section DS1 is connected to the data input/output buffer 6 by way of an internal data input/output line (I/O line) and stores an externally input data to be written or a read out data to be externally output, while the data storage section DS2 stores the detection outcome of a write verify operation for confirming the threshold value of a memory cell after a write operation and the data storage section DS3 temporarily stores the data of a memory cell at the time of writing it and at the time of reading it.

FIG. 7 is a graph illustrating the relationship between a multi-valued data and the threshold value of a memory cell of the first embodiment of multi-value flash memory according to the invention.

Now, the operation of the embodiment of multi-valued flash memory according to the invention and having the above described configuration will be described below by referring to FIG. 7. Assume that each memory cell of this embodiment is adapted to store two bits or a four-valued data. It will be appreciated that a 2-bit data is "11", "10", "01" or "00". The two bits belong respectively to different row addresses (different pages).

A four-valued data is stored in a memory cell with different threshold values. Referring to FIG. 7,



assume that a data showing the lowest threshold value (e.g., the threshold voltage is negative) represents "11" and a data showing the second lowest threshold value (e.g., the threshold voltage is positive)

5 represents "10", while a data showing the third lowest threshold value (e.g., the threshold voltage is positive) represents "01" and a data showing the highest threshold value (e.g., the threshold voltage is positive) represents "00".

10           After an erasing operation, the data in the memory cell is "11". If the data of the lower order page written into this memory cell is "0", the state of the memory cell shifts from "11" to "10" as a result of the writing operation. If the data written into this  
15 memory cell is "1", the state of the memory cell remains to be "11".

          Then, the data of the higher order page is written into the memory cell. If the written data is "1", the state of the memory cell remain from "11" or "10". If  
20 the written data is "0", the state of the memory cell shift either from "11" to "01" or from "10" to "00".

          During a write operation, the data written into a memory cell is read out and a so-called write verify operation is conducted to verify if the writing  
25 operation is satisfactory.

          The data read out by the sense amplifier is regarded as "11" if the threshold value is not higher

than 0V and as "10" if the threshold value is not lower  
than 0V and not higher than 1V, whereas the data is  
regarded as "01" if the threshold value is not lower  
than 1V and not higher than 2V and as "00" if the  
5 threshold value is not lower than 2V.

Thus, four-value threshold values are used for  
storing a 2-bit data in a memory cell. In actual  
devices, the performance of the memory cells can vary  
from memory cell to memory cell and hence their  
10 threshold values can also vary. If they vary to a  
large extent, it will be no longer possible to identify  
the data stored in each memory cell and a wrong data  
may be read out.

This embodiment of multi-valued flash memory is  
15 adapted to suppress dispersion of threshold value in  
a manner as indicated by a solid line in FIG. 7 unlike  
the dispersion of threshold value observed in known  
flash memories as indicated by broken lines in FIG. 7.  
This point will be describe in detail to below.

20 Table 1 shows typical voltages of various parts of  
the first embodiment of multi-valued flash memory in  
erase, write, read and write verify operations. Note  
that, the values shown in Table 1 are obtained when the  
word line WL2 and the even-numbered bit lines BL<sub>e</sub> are  
25 selected for write and read operations.

Table 1

	Erase	First step write	Second step write	Write inhibit	"10" read	"01" read	"00" read
Ble	Floating	0V	0.4V	Vdd	H or L	H or L	H or L
BLo	Floating	Vdd	Vdd	Vdd	0V	0V	0V
SGD	Floating	Vdd	Vdd	Vdd	4.5V	4.5V	4.5V
WL3	0V	10V	10V	10V	4.5V	4.5V	4.5V
WL2	0V	Vpgm	Vpgm	Vpgm	0V	1V	2V
WL1	0V	0V	0V	0V	4.5V	4.5V	4.5V
WL0	0V	10V	10V	10V	4.5V	4.5V	4.5V
SGS	Floating	0V	0V	0V	4.5V	4.5V	4.5V
C-source	Floating	0V	0V	0V	0V	0V	0V
C-p-well	20V	0V	0V	0V	0V	0V	0V

(Continued)

Table 1

	"10" first step write verify	"10" second step write verify	"01" first step write verify	"01" second step write verify	"00" first step write verify	"00" second step write verify
BLe	H or L	H or L	H or L	H or L	H or L	H or L
BLo	0V	0V	0V	0V	0V	0V
SGD	4.5V	4.5V	4.5V	4.5V	4.5V	4.5V
WL3	4.5V	4.5V	4.5V	4.5V	4.5V	4.5V
WL2	0.2V	0.4V	1.2V	1.4V	2.2V	2.4V
WL1	4.5V	4.5V	4.5V	4.5V	4.5V	4.5V
WL0	4.5V	4.5V	4.5V	4.5V	4.5V	4.5V
SGS	4.5V	4.5V	4.5V	4.5V	4.5V	4.5V
C-source	0V	0V	0V	0V	0V	0V
C-p-well	0V	0V	0V	0V	0V	0V

For an erase operation, 20V and 0V are supplied respectively to the p-type well 12 (well line C-p-well) and all the word lines WL0 of the selected block. Electrons are discharged from the floating gates FG  
5 of all the memory cells M of the block so that the threshold value becomes negative to show a state of "11". While the word lines and the bit lines BL of the unselected blocks are brought to an electrically floating state, they show a voltage level close to 20V  
10 as a result of the capacitive coupling with the p-type well 12.

For writing a data, a first step operation, a second step operation and a write inhibiting operation are conducted sequentially. Firstly, program voltage  
15 (write voltage) Vpgm of about 14V to 20V is supplied to the selected word line WL2. A high voltage such as 10V is supplied to each of the unselected word lines, including, say, the word line WL3, of the memory cells located at the bit line side relative to the selected  
20 memory cells in order to make the memory cells connected to the word line WL3 electrically conductive. On the other hand, a low voltage such as 0V is supplied to each of the unselected word lines, including, say the word line WL1, of the memory cells located at the  
25 side of the well line C-p-well relative to the selected memory cells in order make the memory cells connected to the word line WL1 electrically non-conductive.

The selected bit lines BLe is supplies a voltage such as 0V. As a result, the 0V supplied to the selected bit lines BLe are transferred to the drains of the selected memory cells and the electric potential of the floating gates FG is raised by the capacitive coupling of the control gates CG and that of the floating gates FG so that electrons are injected into the floating gates FG from the drain by way of the tunnel oxide film (the tunnel oxide film 16 of FIG. 5A) due to the tunneling phenomenon and the threshold value is rapidly raised (the first step write operation). The voltage of the bit lines BLe is raised to 0.4V to suppress the rate at which the threshold value rises in a write operation (the second step write operation). The bit lines BLe are made to show a sufficiently high voltage, e.g., the supply voltage Vdd (up to 3V) for completely blocking the rise of the threshold value (write inhibition).

A read operation is conducted by sequentially supplying different read voltages (0V, 1V, 2V) to the selected word line WL2. A voltage that makes the unselected memory cells electrically conductive, typically 4.5V, is supplied to the unselected remaining word lines. If the threshold value of the selected memory cells is lower than the read voltage, the bit lines BLe and the common source line C-source are made electrically communicative with each other so that

an electric current flows through them to bring the electric potential of the bit lines BLe to a relatively low level, or level L. If, on the other hand, the threshold value of the selected memory cells is higher  
5 the read voltage, the bit lines BLe and the common source line C-source are made electrically non-communicative with each other to bring the electric potential of the bit lines BLe to a relatively high level, or level H. The read voltage is typically  
10 made equal to 0V and a read operation is conducted (to read "10") for checking if the electric potential of a memory cell is higher than the threshold value corresponding to the state of "10" or not. The read voltage is typically made equal to 1V and a read  
15 operation is conducted (to read "01") for checking if the electric potential of a memory cell is higher than the threshold value corresponding to the state of "01" or not. The read voltage is typically made equal to 2V and a read operation is conducted (to read "00") for  
20 checking if the electric potential of a memory cell is higher than the threshold value corresponding to the state of "00" or not.

A data is written into a memory cell in the state of "10" so as to make the threshold value not smaller  
25 than 0.4V in order to provide a read margin of 0.4V for the read voltage of 0V. Thus, the operation of writing "10" is inhibited when the threshold value of the

memory cell has got to 0.4V as a result of a write verify operation.

Conventional devices comparable to this embodiment are only adapted to check if the threshold value has  
5 got to 0.4V or not so that the threshold value shows a relatively broad distribution width as shown in FIG. 7.

To the contrary, this embodiment of the present invention is adapted to check if the threshold value  
10 has got to a level slightly lower than the target threshold value or not and the rate at which the threshold value rises is suppressed in the second step write operation. Therefore, it is now possible to narrow the distribution width of the threshold  
15 value as indicated by the solid line in FIG. 7. The above description also applies to the states of "01" and "00".

A write verify operation is conducted by sequentially supplying different verify voltages, e.g.,  
20 0.2V, 0.4V, 1.2V, 1.4V, 2.2V, 2.4V to the selected word line WL2. If the threshold value of the selected memory cells is lower than the verify voltage, the bit lines BLe and the common source line C-source are made electrically communicative with each other so that  
25 an electric current flows through them to bring the electric potential of the bit lines BLe to a relatively low level, or level L. If, on the other hand, the



threshold value of the selected memory cells is higher than the verify voltage, the bit lines BL<sub>e</sub> and the common source line C-source are made electrically non-communicative with each other to bring the electric potential of the bit lines BL<sub>e</sub> to a relatively high level, or level H.

If the target threshold value of the memory cell is 0.4V, the verify voltage is reduced typically to 0.2V for a write verify operation in order to check if the threshold value of the memory cell is higher than a level slightly lower than the target threshold value, which is 0.2V in this embodiment, or not (the first step operation of write verify "10"). The verify voltage is made equal to 0.4V and a write verify operation is conducted in order to check if the threshold value of the memory cell is higher than 0.4 or not (the second step operation of write verify "10").

If the target threshold value of the memory cell is 1.4V, the verify voltage is reduced typically to 1.2V for a write verify operation in order to check if the threshold value of the memory cell is higher than a level slightly lower than the target threshold value, which is 1.2V in this embodiment, or not (the first step operation of write verify "01"). The verify voltage is made equal to 1.4V and a write verify operation is conducted in order to check if the

threshold value of the memory cell is higher than 1.4V or not (the second step operation of write verify "01").

5 If the target threshold value of the memory cell is 2.4V, the verify voltage is reduced to 2.2V for a write verify operation in order to check if the threshold value of the memory cell is higher than a level slightly lower than the target threshold value, which is 2.2V in this embodiment, or not (the first  
10 step operation of write verify "00"). The verify voltage is made equal to 2.4V and a write verify operation is conducted in order to check if the threshold value of the memory cell is higher than 2.4 or not (the second step operation of write  
15 verify "00").

FIG. 8 is a graph illustrating the changing threshold value of memory cells of a known flash memory and a data writing method adapted to use such a changing threshold value. In FIG. 8, the small white  
20 squares indicate the threshold value and the write control voltage (the voltage of the bit line BL) to be supplied to a memory cell where a data can be easily written, whereas the small black squares indicate the threshold value and the write control voltage (the  
25 voltage of the bit line BL) to be supplied to a memory cell where a data can be hardly written. The two memory cells stores the data of a same page. The data

are erased from both of them in the initial state and they show a negative threshold value.

The write voltage  $V_{pgm}$  is divided into a number of pulses and the pulses are made to rise stepwise typically by 0.2V at a time. In other words, the write voltage  $V_{pgm}$  increased with a stepwise increment  $\Delta V_{pgm}$  of 0.2V per pulse.

As the voltage of the bit line BL that is the write control voltage is made equal to 0V, the threshold value rises at a rate of 0.2V/pulse which is equal to the increment of the write voltage  $V_{pgm}$  after several pulses. A write verify operation is conducted after the application of each write pulse and the write operation is inhibited at each memory cell whose threshold value, becomes to a bit line voltage  $V_{dd}$  of the memory cell detected to have got to the level of the write verify voltage. Thus, the threshold value shows a distribution width of 0.2V.

FIG. 9 is a graph illustrating the changing threshold value of a memory cell of the first embodiment of multi-value flash memory according to the invention and a data writing method adapted to use such a changing threshold value. As in the case of FIG. 8, the small white squares indicate the threshold value and the write control voltage (the voltage of the bit line BL) to be supplied to a memory cell where a data can be easily written, whereas the small black squares

indicate threshold values and a write control voltage (the voltage of the bit line BL) to be supplied to a memory cell where a data can be hardly written.

5 The two memory cells stores the data of the respective columns of a same page. The data are erased from both of them in the initial state and they show a negative threshold value.

The write voltage  $V_{pgm}$  is divided into a number of pulses and the pulses are made to rise stepwise typically by 0.2V at a time. In other words, the write  
10 voltage  $V_{pgm}$  increases with a stepwise increment  $Dv_{pgm}$  of 0.2V per pulse.

The voltage of the bit line BL that is the write control voltage is made equal to 0V and a first step  
15 write operation is conducted. In the first step write operation, the threshold value rises at a rate of 0.2V/pulse which is equal to the increment of the write voltage  $V_{pgm}$  after the supplied several pulses. A first step write verify operation or a second step  
20 write verify operation is conducted after the application of each write pulse.

The voltage of the bit line of the memory cell whose threshold value has got to the first step write verify voltage is subsequently increased to 0.4V and  
25 the second step write operation is conducted on a memory cell by memory cell basis. The voltage of the bit line of the memory cell whose threshold value has

got to the second step write verify voltage is subsequently brought to Vdd to inhibit any write operation on a memory cell by memory cell basis.

In the second step write operation, the rising  
5 rate of the threshold value is held lower than the 0.2V/pulse of the first step write operation for several pulses. In other words, while the voltage of the bit lines BL, or the write control voltage, is 0V in the first step write operation, it rises to 0.4  
10 in the second step write operation. Therefore, it is more difficult to write data in the second step write operation than in the first step write operation. The rising rate of the threshold value in the second step write operation is typically held within a range  
15 between 0V/pulse and 0.05V/pulse. In other words, the threshold value shows a distribution width of as small as 0.05V in the second step write operation.

If the write pulse width is 20  $\mu$ sec. and the time required for a write verify operation is 5  $\mu$ sec.,  
20 the duration of a write operation is conventionally  $(20 \mu\text{sec.} + 5 \mu\text{sec.}) \times 18 \text{ pulses} = 450 \mu\text{sec.}$

Conventionally, the voltage increment  $Dv_{pgm}$  of write voltage  $V_{pgm}$  needs to be made equal to 0.05V, or a quarter of 0.2V, in order to realize a threshold  
25 value distribution width of 0.05V. Then, the duration of a write operation is  $450 \mu\text{sec} \times 4 = 1800 \mu\text{sec.}$

On the other hand, with this embodiment, as

shown in FIG. 9, it is possible to realize a threshold value distribution width of 0.05V by using a voltage increment  $Dv_{pgm}$  of 0.2V/pulse so that the duration of a write time is  $(20 \mu\text{sec.} + 5 \mu\text{sec.} + 5 \mu\text{sec.}) \times$   
5  $20 \text{ pulses} = 600 \mu\text{sec.}$

Thus, the duration of the write operation necessary for realizing a threshold value distribution width of 0.05V in this embodiment is reduced to a third of that of the above known device.

10 "10" is written by using a "10" first step write verify voltage and a "10" second step write verify voltage respective for first step write verify voltage and for the second step write verify voltage.

FIG. 10 is a graph illustrating the method for  
15 writing a higher order page data into a same memory cell and the change with time of the threshold value of the memory of the first embodiment. As in the case of FIGS. 8 and 9, the small white squares indicate the threshold value and the write control voltage (the  
20 voltage of the bit line BL) to be supplied to a memory cell where a data can be easily written, whereas the small black squares indicate threshold values and a write control voltage (the voltage of the bit line BL) to be supplied to a memory cell where a data can be  
25 hardly written. The two memory cells stores the data of the respective columns of a same page.

The data in the memory cell whose write control

voltage is indicated by white squares, where a data can be easily written, is erased in the initial state and the memory cell shows a negative threshold value. Assume that a data is written in the memory cell to make it show to show a "01" state. A data is already written in the memory cell whose write control voltage is indicated by black squares to make it show a "10" state in the initial state. Assume that a data is written to the memory cell to make it show a "00" state.

The write voltage  $V_{pgm}$  is divided into a number of pulses and the pulses are made to rise stepwise typically by 0.2V at a time. In other words, the write voltage  $V_{pgm}$  increases with a stepwise increment  $\Delta V_{pgm}$  of 0.2V per pulse.

The voltage of the bit line BL that is the write control voltage is made equal to 0V and a first step write operation is conducted. In the first step write operation, the threshold value rises at a rate of 0.2V/pulse which is equal to the increment of the write voltage  $V_{pgm}$  after several pulses. A "01" first step write verify operation is conducted after the application of each write pulse. After the write operation using a threshold value slightly lower than the target threshold value, a "01" second step write verify operation is conducted after the application of each write pulse. Thereafter, a "00" first step write

verify operation and a "00" second step write verify operation are conducted.

When the threshold value of the memory cell indicated by white squares is detected to have got to the "01" first step write verify voltage, subsequently the bit line voltage is made equal to 0.4V and the process proceeds to the second step write operation. When the threshold value of the memory cell indicated by black squared is detected to have got to the "00" first step write verify voltage, subsequently the bit line voltage is made equal to 0.4V and the process proceeds to the second step write operation.

Furthermore, when the threshold value of the memory cell indicated by white squares is detected to have got to the "01" second step write verify voltage, subsequently the bit line voltage is made equal to Vdd and the write operation is inhibited. Finally, when the threshold value of the memory cell indicated by black squares is detected to have got to the "00" second step write verify voltage, subsequently the bit line voltage is made equal to Vdd and the write operation is inhibited.

After the second step write operation starts for both the data "01" and the data "00", the increment of the threshold value is typically held within a range between about 0V/pulse and 0.05V/pulse for several pulses of the write voltage. Therefore, the threshold



value shows only a distribution width of 0.05V.

FIG. 11 is a graph illustrating the signal waveforms of different parts of the first embodiment of flash memory according to the invention when writing  
5 a lower order page data into a single memory cell.

Referring to FIG. 11, the write step continues from time  $tp_0$  to time  $tp_7$ . A write pulse is applied during this period. The "10" first step write verify operation continues from time  $t_{fv_0}$  to time  $t_{fv_6}$ .  
10 Then, the period of time from time  $t_{sv_0}$  to time  $t_{sv_6}$  is assigned to the "10" second step write verify operation. In this instance, it is assumed that the word line WL2 and the even-numbered bit lines BLe are selected.

15 In the write step, the voltage of the bit lines BLe that is the write control voltage is brought to 0V for the first step write operation and to 0.4V for the second step write operation, whereas it is brought to Vdd (e.g., 2.5V) when any write operation is  
20 inhibited.

In each write verify period, firstly the bit lines BLe is charged typically to 0.7V. Thereafter, when the selected word line WL2 has gets to the write verify voltage, the bit lines BLe is held to 0.7V if the  
25 threshold value of the memory cell has got to the write verify voltage but the voltage of the bit lines BLe is reduced toward 0V if the threshold value of the memory

cell has not got to the write verify voltage. If the threshold value of the memory cell has got to the write verify voltage or not can be detected by observing the voltage of the bit lines BL<sub>e</sub> by means of a sense amplifier at timing of time tfv4 or tsv4. If the threshold value of the memory cell has got to the write verify voltage, the detecting operation is successfully completed.

FIG. 12 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention when writing a lower order page data into a single memory cell.

The control operation starts with receiving a data input command from the host and placing the data input command in the state machine 8 (S1). Then, the operation proceeds to receiving an address data from the host and placing the address in the state machine 8 to select the page to be used for a write operation (S2). Thereafter, the operation proceeds to a step of receiving data to be written in a page and storing them correspondingly in the respective data storage sections DS1 (S3). Subsequently, the operation proceeds to a step of receiving a write command issued from the host and placing the write command in the state machine 8 (S4). As the write command is placed, the operation of Steps S5 through S16 is automatically started by the state machine 8 in the inside.

The data stored in the data storage sections DS1 are copied respectively to the corresponding data storage sections DS2 (S5). Thereafter, 12V is selected for the initial value of the write voltage  $V_{pgm}$  and the write counter PC is set to 0 (S6). If the data in the data storage sections DS1 are "0"s and the data in the data storage sections DS2 are also "0"s, they indicate a first step write operation and, therefore, the voltage of the bit lines BLe that is the write control voltage is reduced to 0V. If, on the other hand, the data in the data storage sections DS1 are "0"s and the data in the data storage sections DS2 are "1"s, they indicate a second step write operation and, therefore, the voltage of the bit lines BLe that is the write control voltage is brought to 0.4V. If, finally, the data in the data storage sections DS1 are "1"s and the data in the data storage sections DS2 are also "1"s, they indicate write inhibition and, therefore, the voltage of the bit lines BLe that is the write control voltage is brought to Vdd (S7).

Then, the operation proceeds to the write step of applying a write pulse to the memory cells for storing the data of a page by using the selected write voltage  $V_{pgm}$  and the write control voltage (S8). In the next step, if all the data stored in the data storage sections DS2 are "1"s or not is checked and, if they are all "1"s, it is determined that the status of the

first step is satisfactory whereas, if all the data stored in the data storage sections DS2 are not "1"s, it is determined that the status of the first step is not satisfactory (S9). As will be described

5 hereinafter, if all the data stored in the data storage sections DS2 are "1"s, there is no memory cell where the first step write operation is conducted in the preceding write step (S8).

If the status of the first step is satisfactory,  
10 a "10" first step write verify operation is started (S10) and the data of the data storage sections DS2 corresponding to only the memory cells where the detection outcome is satisfactory out of the memory cells for storing the data of a page are shifted from  
15 "0"s to "1"s. The data storage sections DS2 storing "1"s are made to keep on storing "1"s.

When the status of the first step is satisfactory or when the "10" first step write verify operation is completed, a "10" second step write verify operation is  
20 started (S11). The data of the data storage sections DS1 corresponding to only the memory cells where the detection outcome is satisfactory out of the memory cells for storing the data of a page are shifted from "0"s to "1"s. The data storage sections DS1 storing  
25 "1"s are made to keep on storing "1"s.

After the "10" second step write verify operation, if all the data stored in the data storage sections DS1

are "1"s or not is checked and, if they are all "1"s, it is determined that the status of the second step is satisfactory whereas, if all the data stored in the data storage sections DS2 are not "1"s, it is  
5 determined that the status of the second step is not satisfactory (S12). If the status of the second step is satisfactory, it is judged that the write operation has completed successfully and the status of the write operation is rated as satisfactory to terminate the  
10 write operation (S13).

If, on the other hand, the status of the second step is not satisfactory, the write counter PC is checked (S14). If the reading of the write counter PC is not less than 20, it is judged that the status of  
15 the write operation is failure and the write operation is terminated unsuccessfully (S15). If the reading of the write counter PC is not greater than 20, the reading of the write counter PC is incremented by one and the write voltage  $V_{pgm}$  is raised by 0.2V (S16).  
20 Then, the operation is moved back to Step S7 and then the write operation of Step S8 is retried. It will be appreciated that the norm for the write operation is not necessarily be 20 and some other norm may be selected if appropriate.

25 Table 2 shows the relationship between the data of the data storage sections DS1 and DS2 before and after the "10" first step write verify operation and the

threshold value ( $V_t$ ) of the corresponding memory cells of the write algorithm illustrated in FIG. 12.

Table 2

DS1/DS2 data DS1/DS2 after n-th "10" first step write verify		Memory cell threshold value $V_t$	
		When lower than 0.2V	When higher than 0.2V
DS1/DS2 data DS1/DS2 before n-th "10" first step write verify	0/0	0/0	0/1
	0/1	0/1	0/1
	1/1	1/1	1/1

Immediately before the n-th "10" first step write verify operation, the data of the data storage sections DS1 and DS2 are one of the combinations of 0/0, 0/1 and 1/1. The combination of 0/0 indicates that the  
5 threshold value of the memory cells has not got to the "10" first step write verify voltage by the n-1-th write step. The combination of 0/1 indicates that the threshold value of the memory cells has got to the "10" first step write verify voltage but not to the "10"  
10 second step write verify voltage by the n-1-th write step. The combination of 1/1 indicates that the threshold value of the memory cells has got to the "10" second step write verify voltage by the n-1-th write step. It is not possible that the threshold value of  
15 the memory cells has got to the "10" second step write verify voltage but not to the "10" first step write verify voltage by the n-1-th write step so that the combination of 1/0 does not exist in this embodiment.

Immediately before the first "10" first step  
20 write verify operation, the data of the data storage sections DS1 and DS2 are either of the combinations of 0/0 and 1/1.

If the threshold value of the memory cells has not got to 0.2V which is the "10" first step write verify  
25 voltage by the n-th write step, the detection outcome of the "10" first step write verify operation is not satisfactory so that the data in the data storage



sections DS2 are not changed. If, on the other hand,  
the threshold value of the memory cells has got to  
0.2V, the detection outcome of the "10" first step  
write verify operation is satisfactory so that the data  
5 in the data storage sections DS2 are shifted to "1"s.  
The data storage sections DS2 storing "1"s are made to  
keep on storing "1"s.

Table 3 shows the relationship between the data of  
the data storage sections DS1 and DS2 before and after  
10 the "10" second step write verify operation and the  
threshold value of the corresponding memory cells of  
the write algorithm illustrated in FIG. 12.

Table 3

DS1/DS2 data DS1/DS2 after n-th "10" second step write verify		Memory cell threshold value Vt	
		When lower than 0.4V	When higher than 0.4V
DS1/DS2 data DS1/DS2 before n-th "10" second step write verify	0/0	0/0	-
	0/1	0/1	1/1
	1/1	1/1	1/1

Immediately before the n-th "10" second step write verify operation, the data of the data storage sections DS1 and DS2 are one of the combinations of 0/0, 0/1 and 1/1. The combination of 0/0 indicates that the  
5 threshold value of the memory cells has not got to the "10" first step write verify voltage after the end of the n-th write step. The combination of 0/1 indicates that the threshold value of the memory cells has got to the "10" first step write verify voltage by the n-th  
10 write step but not to the "10" second step write verify voltage by the n-1th write step. The combination of 1/1 indicates that the threshold value of the memory cells has got to the "10" second step write verify voltage by the end of the n-1-th write step.

15 It is not possible that the threshold value of the memory cells has got to the "10" second step write verify voltage by the n-1th write step but not to the "10" first step write verify voltage by the n-th write step so that the combination of 1/0 does not exists in  
20 this embodiment.

If the threshold value of the memory cells has not got to 0.4V which is the "10" second step write verify voltage by the n-th write step, the detection outcome of the "10" second step write verify operation is not  
25 satisfactory so that the data in the data storage sections DS1 are not changed. If, on the other hand, the threshold value of the memory cells has got to

0.4V, the detection outcome of the "10" second step  
write verify operation is satisfactory so that the data  
in the data storage sections DS1 are shifted to "1"s.  
The data storage sections DS2 storing "1"s are made to  
5 keep on storing "1"s. The combination of 0/0 will not  
be changed by the "10" second write verify operation.

FIG. 13 is a flow chart schematically illustrating  
the control algorithm of the first embodiment of flash  
memory according to the invention when writing a higher  
10 order page data into a memory cell.

Referring to FIG. 13, the control operation starts  
with receiving a data input command from the host and  
placing the data input command in the state machine 8  
(S1). Then, the operation proceeds to receiving  
15 an address data from the host and placing the address  
in the state machine 8 to select the page to be used  
for a write operation (S2). Thereafter, the operation  
proceeds to a step of receiving data to be written in a  
page and storing them correspondingly in the respective  
20 data storage sections DS1 (S3). Subsequently, the  
operation proceeds to a step of receiving a write  
command issued from the host and placing the write  
command in the state machine 8 (S4). As the write  
command is placed, the operation of Steps S5 through  
25 S20 is automatically started by the state machine 8 in  
the inside.

Firstly, a "10" write operation is started (S5)

and the operation is satisfactory (the data of the memory cells are "1"s, "0"s are stored in the corresponding data storage sections DS3. If the operation is not satisfactory, "1" are stored in the corresponding data storage sections DS3. Thereafter, the data stored in the data storage sections DS1 are copied respectively to the corresponding storage sections DS2 (S6). Then, 14V is selected for the initial value of the write voltage  $V_{pgm}$  and the write counter PC is set to 0 (S7). If the data in the data storage sections DS1 are "0"s and the data in the data storage sections DS2 are also "0"s, they indicate a first step write operation and, therefore, the voltage of the bit lines BL that is the write control voltage is set to 0V. If, on the other hand, the data in the data storage sections DS1 are "0"s and the data in the data storage sections DS2 are "1"s, they indicate a second step write operation and, therefore, the voltage of the bit lines BL that is the write control voltage is set to 0.4V. If, finally, the data in the data storage sections DS1 are "1"s and the data in the data storage sections DS2 are also "1"s, they indicate write inhibition and, therefore, the voltage of the bit lines BL that is the write control voltage is set to  $V_{dd}$  (S8). Then, the operation proceeds to the write step of applying a write pulse to the memory cells for storing the data of a page by using the selected write

voltage  $V_{pgm}$  and the write control voltage (S9).

In the next step, in all the data storage circuits  
20 where "0"s are stored in the data storage sections  
DS3, it is checked if all the data stored in the data  
5 storage sections DS2 are "1"s or not and, if they are  
all "1"s, it is determined that the status of the "00"  
first step is satisfactory whereas, if all the data  
stored in the data storage sections DS2 are not "1"s,  
it is determined that the status of the "00" first step  
10 is not satisfactory (S10). If all the data stored in  
the data storage sections DS2 are "1"s, there is no  
memory cell where the "00" first step write operation  
is conducted in the preceding write step (S9).

If the status of the "00" first step is not  
15 satisfactory, a "00" first step write verify operation  
is started (S11) and the data of the data storage  
sections DS2 corresponding to only the memory cells  
where the detection outcome is satisfactory out of  
the memory cells for storing the data of a page are  
20 shifted from "0"s to "1"s, provided that the data in  
the data storage sections DS3 are "0". The data  
storage sections DS2 storing "1"s are made to keep on  
storing "1"s.

When the status of the "00" first step is  
25 satisfactory or when the "00" first step write verify  
operation is completed, a "00" second step write verify  
operation is started (S12). The data of the data

storage sections DS1 corresponding to only the memory cells where the detection outcome is satisfactory out of the memory cells for storing the data of a page are shifted from "0"s to "1"s, provided that the data in the data storage section DS3 are "0"s. The data storage sections DS1 storing "1"s are made to keep on storing "1"s.

Thereafter, in all the data storage circuits 20 where "0"s are stored in the data storage sections DS3, it is checked if all the data stored in the data storage sections DS2 are "1"s or not is checked, if they are all "1"s, it is determined that the status of the "01" first step is satisfactory whereas, if all the data stored in the data storage sections DS2 are not "1"s, it is determined that the status of that step is not satisfactory (S13). As will be described hereinafter, if all the data stored in the data storage sections DS2 are "1"s, there is no memory cell where the first step write operation is conducted in the preceding write step (S9).

If the status of the "01" first step is not satisfactory, a "01" first step write verify operation is started (S14) and, in all the data storage circuits 20 where "0"s are stored in the data storage sections DS3, the data of the data storage sections DS2 corresponding to only the memory cells where the detection outcome is satisfactory out of the memory

cells for storing the data of a page are shifted from  
"0"s to "1"s, provided that the data in the data  
storage sections DS3 are "0". The data storage  
sections DS2 storing "1"s are made to keep on  
5 storing "1"s.

When the status of the "01" first step is  
satisfactory or when the "10" first step write verify  
operation is completed, a "10" second step write verify  
operation is started (S15). Then, in all the data  
10 storage circuits 20 where "0"s are stored in the data  
storage sections DS3, the data of the data storage  
sections DS1 corresponding to only the memory cells  
where the detection outcome is satisfactory out of the  
memory cells for storing the data of a page are shifted  
15 from "0"s to "1"s. The data storage sections DS1  
storing "1"s are made to keep on storing "1"s.

After the "01" second step write verify operation,  
if all the data stored in the data storage sections DS1  
are "1"s or not is checked and, if they are all "1"s,  
20 it is determined that the status of the second step is  
satisfactory whereas, if all the data are not "1"s, it  
is determined that the status of the second step is not  
satisfactory (S16). If the status of the second step  
is satisfactory, it is judged that the write operation  
25 has completed successfully and the status of the write  
operation is rated as satisfactory to terminate the  
write operation (S17). If, on the other hand, the



status of the second step is not satisfactory, the  
write counter PC is checked (S18). If the reading of  
the write counter PC is not less than 20, it is judged  
that the status of the write operation is failure and  
5 the write operation is terminated unsuccessfully (S19).  
If the reading of the write counter PC is not greater  
than 20, the reading of the write counter PC is  
incremented by one and the write voltage Vpgm is raised  
by 0.2V (S20). Then, the operation is moved back to  
10 Step S8 and then the write operation of Step S9 is  
retried. It will be appreciated that the norm for the  
write operation is not necessarily be 20 and some other  
norm may be selected if appropriate.

Table 4 shows the relationship between the data of  
15 the data storage sections DS1, DS2 and DS3 before and  
after the "10" first step write verify operation and  
the threshold value (Vt) of the corresponding memory  
cells of the write algorithm illustrated in FIG. 13.

Table 4

DS1/DS2/DS3 data DS1/DS2/DS3 after n-th "01" first step write verify	
Memory cell threshold value Vt	
When lower than 1.2V	
DS1/DS2/DS3 data DS1/DS2/D3 before n-th "01" first step write verify	0/0/1
	0/1/1
	1/1/1
	0/0/0
	0/1/0
When higher than 1.2V	
	0/1/1
	0/1/1
	1/1/1
	0/0/0
	0/1/0
	1/1/0

Immediately before the n-th "01" first step write verify operation, the data of the data storage sections DS1, DS2 and DS3 are one of the combinations of 0/0/1, 0/1/1, 1/1/1, 0/0/0, 0/1/0 and 1/1/0. The combination of 0/0/1 indicates that the threshold value of the memory cells has not got to the "01" first step write verify voltage by the n-1-th write step. The combination of 0/1/1 indicates that the threshold value of the memory cells has got to the "01" first step write verify voltage but not to the "01" second step write verify voltage by the n-1-th write step. The combination of 1/1/1 indicates that the threshold value of the memory cells has got to the "01" second step write verify voltage by the n-1-th write step. It is not possible that the threshold value of the memory cells has got to the "01" second step write verify voltage but not to the "01" first step write verify voltage by the n-1-th write step so that the combination of 1/0/0 does not exist in this embodiment.

If the threshold value of the memory cells has not got to 1.2V which is the "01" first step write verify voltage by the n-th write step, the detection outcome of the "01" second step write verify operation is not satisfactory so that the data in the data storage sections DS2 are not changed. If, on the other hand, the threshold value of the memory cells has got to 1.2V, the detection outcome of the "01" first step

write verify operation is satisfactory so that the data  
in the data storage sections DS2 are shifted to "1"s.  
The data storage sections DS2 storing "1"s are made to  
keep on storing "1"s. The combinations of 0/0/0, 0/1/0  
5 and 1/1/0 do not constitute any objects of the first  
step write verify operation so that they are not  
changed.

Table 5 shows the relationship between the data of  
the data storage sections DS1, DS2 and DS3 before and  
10 after the "01" second step write verify operation and  
the threshold value (Vt) of the corresponding memory  
cells of the write algorithm illustrated in FIG. 13.

Table 5

DS1/DS2/DS3 data DS1/DS2/DS3 after n-th "01" second step write verify		Memory cell threshold value Vt	
		When lower than 1.4V	When higher than 1.4V
DS1/DS2/DS3 data DS1/DS2/D3 before n-th "01" second step write verify	0/0/1	0/0/1	-
	0/1/1	0/1/1	1/1/1
	1/1/1	1/1/1	1/1/1
	0/0/0	0/0/0	0/0/0
	0/1/0	0/1/0	0/1/0
	1/1/0	1/1/0	1/1/0

Immediately before the n-th "01" second step write verify operation, the data of the data storage sections DS1, DS2 and DS3 are one of the combinations of 0/0/1, 0/1/1, 1/1/1, 0/0/0, 0/1/0 and 1/1/0. The combination of 0/0/1 indicates that the threshold value of the memory cells has not got to the "01" first step write verify voltage after the n-th write step. The combination of 0/1/1 indicates that the threshold value of the memory cells has got to the "01" first step write verify voltage by the n-th write step but not to the "01" second step write verify voltage by the n-1-th write step. The combination of 1/1/1 indicates that the threshold value of the memory cells has got to the "01" second step write verify voltage by the n-1-th write step. It is not possible that the threshold value of the memory cells has got to the "01" second step write verify voltage by the n-1-th write step but not to the "01" first step write verify voltage by the n-th write step so that the combination of 1/0/1 does not exists in this embodiment.

If the threshold value of the memory cells has not got to 1.4V which is the "01" second step write verify voltage by the n-th write step, the detection outcome of the "01" second step write verify operation is not satisfactory so that the data in the data storage sections DS1 are not changed. If, on the other hand, the threshold value of the memory cells has got to

1.4V, the detection outcome of the "01" second step write verify operation is satisfactory so that the data in the data storage sections DS1 are shifted to "1"s. The data storage sections DS2 storing "1"s are made  
5 to keep on storing "1"s. The combination of 0/0/1 will not be changed by the "01" second write verify operation. The combinations of 0/0/0, 0/1/0 and 1/1/0 do not constitute any objects of the first step write verify operation so that they are not changed.

10 Table 6 shows the relationship between the data of the data storage sections DS1, DS2 and DS3 before and after the "00" first step write verify operation and the threshold value (Vt) of the corresponding memory cells of the write algorithm illustrated in FIG. 13.

Table 6

DS1/DS2/DS3 data DS1/DS2/DS3 after n-th		"00" first step write verify	
		Memory cell threshold value Vt	
		When lower than 2.2V	When higher than 2.2V
DS1/DS2/DS3 data DS1/DS2/D3 before n-th "00" first step write verify	0/0/1	0/0/1	-
	0/1/1	0/1/1	-
	1/1/1	1/1/1	-
	0/0/0	0/0/0	0/1/0
	0/1/0	0/1/0	0/1/0
	1/1/0	1/1/0	1/1/0



Immediately before the n-th "00" first step write verify operation, the data of the data storage sections DS1, DS2 and DS3 are one of the combinations of 0/0/1, 0/1/1, 1/1/1, 0/0/0, 0/1/0 and 1/1/0. The combination of 0/0/0 indicates that the threshold value of the memory cells has not got to the "00" first step write verify voltage by the n-1-th write step. The combination of 0/1/0 indicates that the threshold value of the memory cells has got to the "00" first step write verify voltage but not to the "00" second step write verify voltage by the n-1-th write step. The combination of 1/1/0 indicates that the threshold value of the memory cells has got to the "00" second step write verify voltage. It is not possible that the threshold value of the memory cells has got to the "00" second step write verify voltage but not to the "00" first step write verify voltage by the n-1-th write step so that the combination of 1/0/0 does not exist in this embodiment.

If the threshold value of the memory cells has not got to 2.2V which is the "00" first step write verify voltage by the n-th write step, the detection outcome of the "00" first step write verify operation is not satisfactory so that the data in the data storage sections DS2 are not changed. If, on the other hand, the threshold value of the memory cells has got to 2.2V by the n-th writer step, the detection outcome of the

"00" first step write verify operation is satisfactory so that the data in the data storage sections DS2 are shifted to "1"s. The data storage sections DS2 storing "1"s are made to keep on storing "1"s. The combinations of 0/0/1, 0/1/1 and 1/1/1 do not constitute any objects of the first step; very operation so that they are not changed.

Table 7 shows the relationship between the data of the data storage sections DS1, DS2 and DS3 before and after the "00" second step write verify operation and the threshold value (Vt) of the corresponding memory cells of the write algorithm illustrated in FIG. 13.

Table 7

DS1/DS2/DS3 data DS1/DS2/DS3 after n-th "00" second step write verify		Memory cell threshold value Vt	
		When lower than 2.4V	When higher than 2.4V
DS1/DS2/DS3 data DS1/DS2/D3 before n-th "00" second step write verify	0/0/1	0/0/1	-
	0/1/1	0/1/1	-
	1/1/1	1/1/1	-
	0/0/0	0/0/0	-
	0/1/0	0/1/0	0/1/0
	1/1/0	1/1/0	1/1/0

Immediately before the n-th "00" second step write verify operation, the data of the data storage sections DS1, DS2 and DS3 are one of the combinations of 0/0/1, 0/1/1, 1/1/1, 0/0/0, 0/1/0 and 1/1/0. The combination of 0/0/0 indicates that the threshold value of the memory cells has not got to the "00" first step write verify voltage after the n-th write step. The combination of 0/1/0 indicates that the threshold value of the memory cells has got to the "00" first step write verify voltage by the n-th write step but not to the "00" second step write verify voltage by the n-1-th write step. The combination of 1/1/0 indicates that the threshold value of the memory cells has got to the "00" second step write verify voltage by the n-1-th write step. It is not possible that the threshold value of the memory cells has got to the "00 second step write verify voltage by the n-1-th write step but not to the "00 first step write verify voltage by the n-th write step so that the combination of 1/0/0 does not exists in this embodiment.

If the threshold value of the memory cells has not got to 2.4V which is the "00" second step write verify voltage by the n-th write step, the detection outcome of the "00" second step write verify operation is not satisfactory so that the data in the data storage sections DS1 are not changed. If, on the other hand, the threshold value of the memory cells has got to

2.4V, the detection outcome of the "00" second step write verify operation is satisfactory so that the data in the data storage sections DS1 are shifted to "1"s. The data storage sections DS1 storing "1"s are made to  
5 keep on storing "1"s. The combination of 0/0/0 will not be changed by the "00" second write verify operation. The combinations of 0/0/1, 0/1/1 and 1/1/1 do not constitute any objects of the first step; very operation so that they are not changed.

10           FIG. 14 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash memory according to the invention for controlling the order of writing data into the blocks.

          Firstly, the word line WL0 is selected and lower  
15 order data are written into a page constituted by a plurality of memory cells connected to even-numbered bit lines. Secondly, lower order data are written into a page constituted by a plurality of memory cells connected to odd-numbered bit lines. Thirdly, higher  
20 order data are written into a page constituted by a plurality of memory cells connected to even-numbered bit lines. Finally, higher order data are written into a page constituted by a plurality of memory cells connected to odd-numbered bit lines. Then, data are  
25 written in a similar manner by sequentially using the remaining word lines WL1, WL2, WL3, ..., observing the above sequence.

With this arrangement, the interference of the floating gates of adjacent memory cells can be minimized. In other words, if a memory cell where a data is written subsequently shifts its state from "11" to "10", from "11" to "01" or from "10" to "00",  
5 a shift from "11" to "00" never takes place. The shift from "11" to "00" raises the threshold value of adjacent memory cells most.

FIG. 15 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash  
10 memory according to the invention when reading the lower order page data stored in a memory cell.

The control operation starts with receiving a read command from the host and placing the read command in the state machine 8 (S1). Then, the operation proceeds to receiving an address data from the host and placing the address in the state machine 8 to select the page to be used for a read operation (S2). As a result of the addressing, the operation of Steps S3 through S5 is  
15 automatically started by the state machine 8 in the inside.

Firstly, a "01" read operation is started (S3). A voltage of 1V is supplied to the word line WL for the "01" read operation. "1" is produced by the reading  
25 operation of the sense amplifier if the threshold value of the memory cell is lower than the "01" data, whereas "0" is produced if the threshold value of the memory

cell is higher than "01" data. The outcome of the read operation is stored in the corresponding data storage section DS3. Thereafter, a "10" read operation is started (S4). A voltage of 0V is supplied to the word line WL for the "10" read operation. "1" is produced by the reading operation of the sense amplifier if the threshold value of the memory cell is lower than the "10" data, whereas "0" is produced if the threshold value of the memory cell is higher than "10" data.

10 The outcome of the read operation is stored in the corresponding data storage section DS2. Lastly, a "00" read operation is started (S5). A voltage of 2V is supplied to the word line WL for the "00" read operation. "1" is produced by the reading operation

15 of the sense amplifier if the threshold value of the memory cell is lower than the "00" data, whereas "0" is produced if the threshold value of the memory cell is higher than "00" data. The lower order page data is produced by a logical operation using the outcome of

20 the "00" read operation and the data stored in the corresponding data storage sections DS2 and DS3 and stored in the corresponding data storage section DS1. The data stored in the data storage section DS1 is output as lower order page data.

25 For example, if the outcome of the operation of reading "01" stored in the data storage section DS3 is "1" and that of the operation of reading "10" stored in

the data storage section DS2 is also "1", "1" is produced by the logical operation using the lower order page data. If the outcome of the operation of reading "01" stored in the data storage section DS3 is "1" and  
5 that of the operation of reading "10" stored in the data storage section DS2 is "0", "0" is produced by the logical operation using the lower order page data. If the outcome of the operation of reading "01" stored in the data storage section DS3 is "0" and that of the  
10 operation of reading "00" is also "0", "0" is produced by the logical operation using the lower order page data. The outcome of the operation of reading "01" stored in the data storage section DS3 is "0" and that of the operation of reading "00" is "1", "1" is  
15 produced by the logical operation using the lower order page data.

In short, the logic circuit for carrying out such logical operations needs to be so arranged that the value of the DS2 is stored in the data storage section  
20 DS1 as lower order page data when DS3 is "1" and the outcome of reading "01" is stored in the data storage section DS1 as lower order page data when DS3 is "0".

FIG. 16 is a flow chart schematically illustrating the control algorithm of the first embodiment of flash  
25 memory according to the invention when reading the higher order page data stored in a memory cell.

The control operation starts with receiving a read



command from the host and placing the read command in the state machine 8 (S1). Then, the operation proceeds to receiving an address data from the host and placing the address in the state machine 8 to select the page to be used for a read operation (S2). As a result of the addressing, the operation of Step S3 is automatically started by the state machine 8 in the inside.

Firstly, a "01" read operation is started in Step S3. The outcome of the reading operation shows upper order page data,, which is stored in the corresponding data storage section DS1. In other words, the outcome of the operation of reading "01" is used as upper order page data. Then, the data in the data storage section DS1 is externally output.

In this way, with the multi-value flash memory of the first embodiment, it is now possible to suppress any undesired increase of write time and reduce the distribution width of a threshold value so as to improve the reliability of the device.

Now, the second embodiment of the invention will be described below.

FIG. 17A is a graph illustrating the signal waveforms in a write step of the first embodiment of flash memory according to the invention as extracted from the signal waveform of FIG. 11. Note that the voltage of the bit lines BL<sub>e</sub> is made equal to 0.4V to carry out a second step write operation. In a write

step of the first embodiment, the write operation is conducted while the voltage of the bit lines BL that is the write control voltage is typically held to 0.4V during all the period of applying a predetermined write voltage (e.g., 18.0V as shown in FIG. 17A) to the selected word line WL.

FIG. 17B is a graph illustrating the signal waveforms in a write step of the second embodiment of flash memory according to the invention. As shown in FIG. 17B, the voltage of the bit lines BL that is the write control voltage is held to 0V for only a predetermined period  $T_{wr}$  out of all the period of applying the write voltage  $V_{pgm}$  to the selected word line WL and subsequently brought to  $V_{dd}$  in order to inhibit any write operation thereafter.

The predetermined period  $T_{wr}$  for which the voltage of the bit lines BL is held to 0V is determined in such a way that the duration of the second step write operation is shorter than that of the first step write operation. Then, the increment of the threshold value for the second step write operation can be made smaller than that of the threshold value for the first step write operation as in the case of the first embodiment.

Thus, with the second embodiment, the effective value of the write control voltage can be made substantially equal to that of the first embodiment where the voltage of the bit lines BL that is the write

control voltage is held to a constant level during the entire write step to consequently bring about the advantages of the first embodiment.

Now, the third embodiment of the invention will be  
5 described below.

FIG. 18 is a graph illustrating the signal waveforms of different parts of the third embodiment of flash memory according to the invention when writing a data into a single memory cell. It will be appreciated  
10 that FIG. 18 corresponds to the waveforms of FIG. 11.

As described above by referring to FIG. 11, with the first embodiment, the voltage of the bit lines is reset to 0V after the end of a first step write verify operation even when it maintains the voltage level  
15 observed immediately after a charging operation and then the bit lines are electrically recharged for a second step write verify operation.

On the other hand, with the third embodiment a write verify operation is conducted in a manner as  
20 described below.

The bit lines BL<sub>e</sub> are electrically charged typically to 0.7V for a first step write verify operation. As the selected word line WL<sub>2</sub> gets to the first step write verify voltage, the bit lines BL<sub>e</sub>  
25 maintain the 0.7V if the threshold value of the memory cell has got to the first step write verify voltage. However, the voltage of the bit lines BL<sub>e</sub> falls toward

0V if the threshold value of the memory cell has not got to the first step write verify voltage. If the threshold value of the memory cell has got to the first step write verify voltage or not can be detected by  
5 observing the voltage of the bit lines BLe by means of a sense amplifier at timing of tfv4 shown in FIG. 18. If the threshold value of the memory cell has got to the write verify voltage, the detecting operation is successfully completed.

10           Thereafter, at timing of tfv5 of tfv3, the voltage of the selected word line WL2 is switched from the first step write verify voltage to the second step write verify voltage. For example, the voltage of the selected word line WL2 may be raised from 0.2V to 0.4V  
15 as shown in FIG. 18. If the threshold value of the memory cell has got to the second step write verify voltage, the 0.7V of the bit lines BLe is maintained. If, on the other hand, the threshold value of the memory cell has not got to the second step write verify  
20 voltage, the voltage of the bit lines BLe falls toward 0V. If the threshold value of the memory cell has got to the second step write verify voltage or not can be checked by detecting the voltage of the bit lines BLe at the timing of tsv4. If the threshold value of the  
25 memory cell has got to the write verify voltage, the outcome of the detection is satisfactory.

The third embodiment provides an advantage of

eliminating the time necessary for charging the bit lines for a second step write verify operation and achieving a higher data writing rate in addition to the advantages of the first embodiment. It will be appreciated that the above description applies to a first or second step write verify operation with data "01" or data "00" by changing the write verify voltage.

While the above embodiments are described in terms of storing a 2-bit data, or a 4-valued data, in a single memory cell, it will be appreciated that embodiments adapted to store a higher valued data in a single memory can easily be realized.

Additional advantages and modifications will readily occur to those skilled in the art. Therefore, the invention in its broader aspects is not limited to the specific details and representative embodiments shown and described herein. Accordingly, various modifications may be made without departing from the spirit or scope of the general inventive concept as defined by the appended claims and their equivalents.